

Wireless Microphones 2 Antennasplitter

ASP 2

Cat. No. 09824

Description

Passive 2 x 1 : 4 antenna splitter. The ASP 2 allows a single pair of antennas to feed up to four EM 500 G2, EM 300 G2 or EM 100 G2 receivers. Incorporates DC distribution for distributing the DC supply voltage of the NT 1 power supply unit to up to four receivers.

By combining two ASP 2, an 8-channel system can be operated with only two antennas.



Features

Easy installation

Technical data

| | |
|---------------------------------|--|
| RF frequency range | 500 870 MHz |
| Attenuation | 10 dB (IN B/OUT B), 14 dB (IN A/OUT A) |
| Dimensions | 212 x 145 x 38 mm |
| Weight | 700 g |
| Operating voltage (stand alone) | 10-16 V DC |

Delivery includes

1 ASP 2 antenna splitter
Operating instructions

Recommended Accessories

| | | |
|-------------------------------------|------------|---------------|
| Mains unit for ASP 2 (EU version) | NT 1 | Cat. No.04786 |
| Mains unit for ASP 2 (UK version) | NT 1-UK | Cat. No.04787 |
| Mains unit for ASP 2 (120V version) | NT 1-120 | Cat. No.04788 |
| Passive Antenne | A 2003-UHF | Cat. No.03658 |
| Omni-directional antenna | A 1031-U | Cat. No.04645 |
| Active directional antenna | A 12AD-UHF | Cat. No.04156 |
| Rack Mount Kit | GA 2 | Cat. No.09823 |